

PHASING DIAGRAM DETECTION LEGEND

DETECTED MOVEMENT

Ø2+6

SIGNAL

FACE

P21,P22

P41,P42

P61,P62

P81,P82

UNDETECTED MOVEMENT (OVERLAP) UNSIGNALIZED MOVEMENT

← − → PEDESTRIAN MOVEMENT

EVP 2 (Ø1+6)
EVP 3 (Ø4+7)

TABLE OF OPERATION All Hands I F D

| W | D:W | D:W | D:W | DR |

	PHASE				
SIGNAL FACE		Ø4+8	E>P Q	E>P 3	エのひ「1
21, 22	G	R	R	R	Υ
41	R	G	R	G	R
42	R	G	R	G	R
61	G	R	G	R	Υ
62	G	R	G	R	Υ
81, 82	R	G	R	R	R
P21, P22	W	D-W	D·W	D·W	DRK
P41. P42	D:W	W	D:W	D:W	DRK

P81, P82

SIGNAL FACE I.D.

А	II Hedds L.E.I	J •
R Y G G	R Y 12"	Accessible Pedestrian Signal
41	21,22	P21, P22

81, 82

4B

P41, P42 P61, P62 P81, P82

DISTANCE SIZE FROM EXTEND DELAY ZONE TURNS PHASE STOPBAR 2A * | 6X40 | 0 | * | X | 2 | Yes | $2B * \mid 6X40 \mid$ * | X | 2 | Yes | 16" 4A * | 6X40 | 0 |* | X | 4 | Yes | * | X | 4 | Yes | $6A \times | 6X40 | 0 |$ * | X | 6 | Yes | 6B * 6X40 * | X | 6 | Yes |

PLANS PREPARED IN THE OFFICE OF:

NC License #F-0102

Raleigh, NC 27601 (919) 677-2000

Kimley Morn

421 Fayetteville Street, Suite 600

DETECTOR

ASC/3 VIDEO DETECTOR INSTALLATION CHART

PROGRAMMING

 $8A * \mid 6X40 \mid 0 \mid * \mid X \mid 8 \mid Yes \mid$ st See Note #11

	 1
GNAL OPERATION	
SPEECH MESSAGE	
Spring, Walk sign is on to cross Spring	
Wait, Wait to cross Spring.	
Corban, Walk sign is on to cross Corban	
Wait, Wait to cross Corban.	
Spring, Walk sign is on to cross Spring	
Wait, Wait to cross Spring.	
Corban, Walk sign is on to cross Corban	
Wait, Wait to cross Corban.	

ASC/3 TIMING CHART						
PHASE						
FEATURE	1	2	4	6	7	8
Min Green *	7	10	7	10	7	7
Walk *	0	7	7	7	0	7
Ped Clear	0	6	12	7	0	10
Veh. Extension *	2.0	2.0	2.0	2.0	2.0	2.0
Max 1 *	30	40	30	40	30	30
Yellow	3.0	3.0	3.0	3.0	3.0	3.0
Red Clear	1.9	2.1	2.6	1.9	2.3	2.3
Actuations B4 Add *	-	-	-	-	-	-
Seconds /Actuation *	-	-	-	-	-	-
Max Initial *	-	-	-	-	-	-
Time Before Reduction *	-	-	-	-	-	-
Time To Reduce *	-	-	-	-	-	_
Minimum Gap	-	-	-	-	-	-
Locking Detector	-	X	-	X	-	_
Recall Position	-	VEH. RECALL	-	VEH. RECALL	-	-

ACCESSIBLE PEDESTRIAN SIGNAL OPERATION

INTERVAL

Flashing Don't Walk / Don't Walk

Flashing Don't Walk / Don't Walk

Walk

Flashing Don't Walk / Don't Walk

Flashing Don't Walk / Don't Walk

* Volume should be set to 5dB over ambient noise level.

* These values may be field adjusted. Do not adjust Min Green and Extension times for phases 2 and 6 lower than what is shown. Min Green for all other phases should not be lower than 4 seconds

Metal Pole #	2 —		
Corban Avenue	P61	P62 P81 81 82	20 MPH -3% Grade
	→ 62 → 10 → 61 → 61		6B <
<u>→</u> <u>2</u> A		21 -	6A ✓
2B (P22 42 20 P41 DD P2 V	22	
20 MPH +3% Grade Met	ral Pole #3	Grade Metal Pole #4	Corban Avenue
	Spring Street	8A SO MPH -2% 6	

ASC/3 EV PREEMPT				
FUNCTION	EVP 2	EVP 3		
Exit Phase(s)	2+6	4+8		
Preempt Override	OFF	OFF		
Delay Time	0	0		
Ped Clear Through Yellow	Y	Y		
Terminate Phases	N	N		
Entrance Walk	1	1		
Entrance Ped Clear	7	10		
Entrance Min Green	1	1		
Entrance Yellow Change	25 . 5*	25.5 *		
Entrance Red Clear	25.5 *	25.5 *		
Minimum Dwell Time	7	7		
Preempt Input Extension Time	0.0	0.0		
Preempt Max Time	120	120		
Exit Yellow Change	25.5 *	25 . 5*		
Exit Red Clear	25.5 *	25 . 5*		

* Allows normal phase times to be used.

2 Phase Fully Actuated W/ Emergency Vehicle Preemption (Concord Signal System)

PROJECT REFERENCE NO. PED UPGRADES

SIG. 5.0

NOTES

- 1. Refer to "Roadway Standard Drawings NCDOT" dated January 2018, "Standard Specifications for Roads and Structures" dated January 2018.
- 2. Do not program signal for late night flashing operation unless otherwise directed by the Engineer.
- 3. Set all detector units to presence mode.
- 4. Locate new cabinet so as not to obstruct sight distance of vehicles turning right on red.
- 5. Omit "WALK" and flashing "DON'T WALK" with no pedestrian calls.
- 6. Program pedestrian heads to countdown the flashing "Don't Walk" time only.
- 7. Pavement markings are existing.
- 8. Program signal heads 41 and 61 to clear to all red before going into preempt.
- 9. Maximum times shown in timing chart are for free-run operation only. Coordinated signal system timing values shall supersede these values.
- 10. Install new cabinet on the existing cabinet foundation.
- 11. Install 360 degree video detection system for vehicle detection. Perform installation according to manufacturer's directions and City engineer-approved mounting locations to accomplish the detection schemes shown on the Signal Design Plans.
- 12. Optical detector 10 calls EVP 2; Optical detector 20 calls EVP 3.
- 13. This intersection features accessible pedestrian signals utilizing a speech walk indication. Refer to section 4E.11 of the 2009 MUTCD for tone rate and frequency requirements.
- 14. Phase 1 and phase 7 used during emergency vehicle preemption only.

	<u></u>	
<u>PROPOSED</u>		EXISTING
\bigcirc	Traffic Signal Head	
O	Modified Signal Head	N/A
\dashv	Sign	\dashv
\downarrow	Pedestrian Signal Head With Push Button & Sign	
0	Metal Pole with Mastarm	
	Video Detection Area	
	Controller & Cabinet	
	Junction Box	
	2-in Underground Conduit	
N/A	Right of Way	
\longrightarrow	Directional Arrow	\longrightarrow
N/A	Curb Ramp	
\sim	Out of Davoment Dataston	

LEGEND

Out of Pavement Detector Signal Upgrade Corban Avenue NORTH CAROLINA High Performance Living Spring Street Cabarrus County PLAN DATE: December 2019 REVIEWED BY: SP Pennington PREPARED BY: DA Waller

REVISIONS

Concord REVIEWED BY: SL Phillips

2/24/2020 SIG. INVENTORY NO. C-9507

032607

DOCUMENT NOT CONSIDERED FINAL UNLESS ALL SIGNATURES COMPLETED

Dual Entry